

# AEC-NASA TECH BRIEF



AEC-NASA Tech Briefs describe innovations resulting from the research and development program of the U.S. AEC or from AEC-NASA interagency efforts. They are issued to encourage commercial application. Tech Briefs are published by NASA and may be purchased, at 15 cents each, from the Clearinghouse for Federal Scientific and Technical Information, Springfield, Virginia 22151.

## Punch-Magnet Delay Eliminated by Modification of Circuit




Fig. 1. Modification when a Breakdown Margin Exists

### The problem:

To increase the reliability of data on paper tape by modification of punch-magnet circuitry. Voltage-damping-diode or diode-resistor networks have been used in the past to protect punch-magnet driver transistors from damage by inductive transients. These damping networks prolonged activation of the magnet by allowing current to remain in it after the driver transistor was turned off; thus the magnet operated improperly.

### The solution:

Reduction of retardation, by the diode-resistor networks, of the current-decay time of the punch magnet by connection of a zener diode in series with the damping network.

### How it's done:

In a magnet driver circuit in which a voltage margin exists between the driver-transistor breakdown voltage and the circuit-supply voltage, a 24-V zener diode is connected in series with the damping network (Fig. 1). Thus the network is effective only when the amplitude of the transient voltage exceeds 24 V. Also a resistive-capacitive network is added in series with the magnet coil, as recommended by the punch manufacturer.

### Notes:

- For punch-driver circuits having no voltage margin, another modification adds an extra magnet-driver stage (Fig. 2).

(continued overleaf)

2. Inquiries may be directed to:

Office of Industrial Cooperation  
Argonne National Laboratory  
9700 South Cass Avenue  
Argonne, Illinois 60439  
Reference: B69-10416

Source: C. E. Cohn  
Reactor Physics Division  
(ARG-10333)

**Patent status:**

Inquiries concerning rights for commercial use of this innovation may be made to:

Mr. George H. Lee, Chief  
Chicago Patent Group  
U.S. Atomic Energy Commission  
Chicago Operations Office  
9800 South Cass Avenue  
Argonne, Illinois 60439




Fig. 2. Modification in the Absence of a Breakdown Margin